



130A Brushless ESC Programmable Options

Programmable Items	Parameter Options								
	1	2	3	4	5	6	7	8	9
1. Running Mode	Forward w/ Brake	Forward/Reverse w/ Brake	Forward & Reverse						
2. Drag Brake Force	0%	5%	10%	20%	40%	60%	80%	100%	
3. Cutoff Voltage	None	2.6V/Cell	2.8V/Cell	3.0V/Cell	3.2V/Cell	3.4V/Cell			
4. Punch (Level)	1	2	3	4	5	6	7	8	9
5. Max Brake Force	25%	50%	75%	100%	Disabled				
6. Max Reverse Force	25%	50%	75%	100%					
7. Initial Brake	Drag Brake	0%	20%	40%					
8. Neutral Range	6%	9%	12%						
9. Timing (Degrees)	0	3.75	7.5	11.25	15	18.75			
10. Motor Rotation	CCW	CW							
11. LiPo Cells	Auto Calc.	2S	3S	4S					

* The blacked out cells with white text are the default settings.



64902

Spektrum Firma 130 Amp ESC SPMXSE1130



130 Amp Brushless Smart ESC Specifications

SPMXSE1130

Cont. Current	130A
LiPo Cells	2 - 4S LiPo / 5 - 12S NiMH
BEC Output	6V @ 5A
Size/Weight	57mm x 37mm (56mm at tabs) x 38mm/ 238g
Battery Connectors	IC5 - 12AWG / 165mm (6.5")

Burst Current	760A
Waterproof	IP67 rated
Motor Connector	4mm Female Bullet
Motor Type	Sensorless Brushless
Telemetry	SRXL2 Compatible Spektrum Smart Technology



64902

Spektrum Firma 130 Amp ESC SPMXSE1130