



150A Brushless ESC Programmable Options

Programmable Items	Parameter Options								
	1	2	3	4	5	6	7	8	9
1. Running Mode	Forward w/ Brake	Forward/Reverse w/ Brake							
2. Drag Brake Force	0%	5%	10%	20%	40%	60%	80%	100%	
3. Cutoff Voltage	Auto (Low)	Auto (Medium)	Auto (High)						
4. Punch (Level)	1	2	3	4	5				
5. Max Brake Force	25%	37.5%	50%	62.5%	75%	87.5%	100%		
6. Max Reverse Force	25%	50%	75%	100%					
7. BEC Voltage	6.0V	7.4V							
8. Neutral Range	6%	9%	12%						
9. Timing (Degrees)	0.0	3.75	7.5	11.25	15.0				
10. Motor Rotation	CCW	CW							
11. LiPo Cells	Auto Calc.	3S	4S	6S					

* The blacked out cells with white text are the default settings.



64209

Spektrum Firma 150 Amp ESC SPMXSE1150



150 Amp Brushless Smart ESC Specifications

SPMXSE1150

Cont. Current	150A
Max Burst Current	950A
LiPo Cells	3 – 6S LiPo / 10 – 20S NiMH
BEC Output	6V/ 7.4V Adjustable @ 5A
Size/Weight	58mmx47.5mmx38.5mm/ 238g

Waterproof	IP67 Rated
Motor Connector	4mm Female Bullet
Battery Input	Dual IC5 (Series), 10 AWG 200mm
Motor Type	Sensorless Brushless
Telemetry	SRXL2 Compatible Spektrum Smart Technology



64209

Spektrum Firma 150 Amp ESC SPMXSE1150